
COMPUTER SCIENCE

2210/11

Paper 1

May/June 2018

MARK SCHEME

Maximum Mark: 75

Published

This mark scheme is published as an aid to teachers and candidates, to indicate the requirements of the examination. It shows the basis on which Examiners were instructed to award marks. It does not indicate the details of the discussions that took place at an Examiners' meeting before marking began, which would have considered the acceptability of alternative answers.

Mark schemes should be read in conjunction with the question paper and the Principal Examiner Report for Teachers.

Cambridge International will not enter into discussions about these mark schemes.

Cambridge International is publishing the mark schemes for the May/June 2018 series for most Cambridge IGCSE™, Cambridge International A and AS Level and Cambridge Pre-U components, and some Cambridge O Level components.

IGCSE™ is a registered trademark.

This document consists of **12** printed pages.

PUBLISHED**Generic Marking Principles**

These general marking principles must be applied by all examiners when marking candidate answers. They should be applied alongside the specific content of the mark scheme or generic level descriptors for a question. Each question paper and mark scheme will also comply with these marking principles.

GENERIC MARKING PRINCIPLE 1:

Marks must be awarded in line with:

- the specific content of the mark scheme or the generic level descriptors for the question
- the specific skills defined in the mark scheme or in the generic level descriptors for the question
- the standard of response required by a candidate as exemplified by the standardisation scripts.

GENERIC MARKING PRINCIPLE 2:

Marks awarded are always **whole marks** (not half marks, or other fractions).

GENERIC MARKING PRINCIPLE 3:

Marks must be awarded **positively**:

- marks are awarded for correct/valid answers, as defined in the mark scheme. However, credit is given for valid answers which go beyond the scope of the syllabus and mark scheme, referring to your Team Leader as appropriate
- marks are awarded when candidates clearly demonstrate what they know and can do
- marks are not deducted for errors
- marks are not deducted for omissions
- answers should only be judged on the quality of spelling, punctuation and grammar when these features are specifically assessed by the question as indicated by the mark scheme. The meaning, however, should be unambiguous.

GENERIC MARKING PRINCIPLE 4:

Rules must be applied consistently e.g. in situations where candidates have not followed instructions or in the application of generic level descriptors.

GENERIC MARKING PRINCIPLE 5:

Marks should be awarded using the full range of marks defined in the mark scheme for the question (however; the use of the full mark range may be limited according to the quality of the candidate responses seen).

GENERIC MARKING PRINCIPLE 6:

Marks awarded are based solely on the requirements as defined in the mark scheme. Marks should not be awarded with grade thresholds or grade descriptors in mind.


Question	Answer	Marks
1	1 mark for each correct answer, in the given order: <ul style="list-style-type: none"> – analogue – digital – denary – 10 – binary – 2 	6

Question	Answer	Marks
2	1 mark for each correct conversion: <ul style="list-style-type: none"> – 42 – 257 – 542 	3

Question	Answer	Marks
3	1 mark for correct register, 3 marks for reason: <ul style="list-style-type: none"> – Register C <p>Any three from:</p> <ul style="list-style-type: none"> – Count the number of 1/0 bits (in each byte/register) – Two bytes/registers have an odd number of 1/0 bits // Two use odd parity – Odd parity must be the parity used – One byte/register has an even number of 1/0 bits // One uses even parity – One with an even number of one bits/even parity is incorrect // Register C should have odd parity 	4

Question	Answer	Marks
4(a)	1 mark for each correct answer: Lossy (compression) Lossless (compression)	2
4(b)	1 mark for correct compression, 3 marks for description: – Lossless (compression) Any three from: – The file can be restored/decompressed to the exact same state it was before compression/ to original – (It is a computer program so) no data can be lost // Lossy would remove data – Will not run correctly (with any other compression) – (Lossless) will give repeating words/sections of word a value// RLE is used // Other valid examples of methods of lossless compression – Value is recorded in an index	4

Question	Answer	Marks														
5	<p>1 mark for each correct line, up to a maximum of 5 marks:</p> <table border="0" style="width: 100%;"> <thead> <tr> <th style="text-align: left; width: 40%;">Component</th> <th style="text-align: left;">Description</th> </tr> </thead> <tbody> <tr> <td style="border: 1px solid black; padding: 5px;">Immediate access store (IAS)</td> <td style="border: 1px solid black; padding: 5px;">Holds data and instructions when they are loaded from main memory and are waiting to be processed.</td> </tr> <tr> <td style="border: 1px solid black; padding: 5px;">Register</td> <td style="border: 1px solid black; padding: 5px;">Holds data temporarily that is currently being used in a calculation.</td> </tr> <tr> <td style="border: 1px solid black; padding: 5px;">Control unit (CU)</td> <td style="border: 1px solid black; padding: 5px;">Holds data or instructions temporarily when they are being processed.</td> </tr> <tr> <td style="border: 1px solid black; padding: 5px;">Accumulator (ACC)</td> <td style="border: 1px solid black; padding: 5px;">Manages the flow of data and interaction between the components of the processor.</td> </tr> <tr> <td style="border: 1px solid black; padding: 5px;">Arithmetic logic unit (ALU)</td> <td style="border: 1px solid black; padding: 5px;">Carries out the calculations on data.</td> </tr> <tr> <td style="border: 1px solid black; padding: 5px;">Bus</td> <td style="border: 1px solid black; padding: 5px;">Pathway for transmitting data and instructions.</td> </tr> </tbody> </table>	Component	Description	Immediate access store (IAS)	Holds data and instructions when they are loaded from main memory and are waiting to be processed.	Register	Holds data temporarily that is currently being used in a calculation.	Control unit (CU)	Holds data or instructions temporarily when they are being processed.	Accumulator (ACC)	Manages the flow of data and interaction between the components of the processor.	Arithmetic logic unit (ALU)	Carries out the calculations on data.	Bus	Pathway for transmitting data and instructions.	5
Component	Description															
Immediate access store (IAS)	Holds data and instructions when they are loaded from main memory and are waiting to be processed.															
Register	Holds data temporarily that is currently being used in a calculation.															
Control unit (CU)	Holds data or instructions temporarily when they are being processed.															
Accumulator (ACC)	Manages the flow of data and interaction between the components of the processor.															
Arithmetic logic unit (ALU)	Carries out the calculations on data.															
Bus	Pathway for transmitting data and instructions.															

Question	Answer	Marks
6(a)	<p>1 mark for each correct logic gate (with the correct direction of input(s))</p> 	6

Question	Answer	Marks																																													
6(b)	<p>4 marks for 8 correct outputs 3 marks for 6 or 7 correct outputs 2 marks for 4 or 5 correct outputs 1 mark for 2 or 3 correct outputs</p> <table border="1" data-bbox="342 384 1361 837"> <thead> <tr> <th data-bbox="342 384 421 432">A</th> <th data-bbox="421 384 499 432">B</th> <th data-bbox="499 384 577 432">C</th> <th data-bbox="577 384 1283 432">Working space</th> <th data-bbox="1283 384 1361 432">X</th> </tr> </thead> <tbody> <tr> <td data-bbox="342 432 421 480">0</td> <td data-bbox="421 432 499 480">0</td> <td data-bbox="499 432 577 480">0</td> <td data-bbox="577 432 1283 480"></td> <td data-bbox="1283 432 1361 480">1</td> </tr> <tr> <td data-bbox="342 480 421 528">0</td> <td data-bbox="421 480 499 528">0</td> <td data-bbox="499 480 577 528">1</td> <td data-bbox="577 480 1283 528"></td> <td data-bbox="1283 480 1361 528">1</td> </tr> <tr> <td data-bbox="342 528 421 576">0</td> <td data-bbox="421 528 499 576">1</td> <td data-bbox="499 528 577 576">0</td> <td data-bbox="577 528 1283 576"></td> <td data-bbox="1283 528 1361 576">1</td> </tr> <tr> <td data-bbox="342 576 421 624">0</td> <td data-bbox="421 576 499 624">1</td> <td data-bbox="499 576 577 624">1</td> <td data-bbox="577 576 1283 624"></td> <td data-bbox="1283 576 1361 624">1</td> </tr> <tr> <td data-bbox="342 624 421 671">1</td> <td data-bbox="421 624 499 671">0</td> <td data-bbox="499 624 577 671">0</td> <td data-bbox="577 624 1283 671"></td> <td data-bbox="1283 624 1361 671">0</td> </tr> <tr> <td data-bbox="342 671 421 719">1</td> <td data-bbox="421 671 499 719">0</td> <td data-bbox="499 671 577 719">1</td> <td data-bbox="577 671 1283 719"></td> <td data-bbox="1283 671 1361 719">1</td> </tr> <tr> <td data-bbox="342 719 421 767">1</td> <td data-bbox="421 719 499 767">1</td> <td data-bbox="499 719 577 767">0</td> <td data-bbox="577 719 1283 767"></td> <td data-bbox="1283 719 1361 767">1</td> </tr> <tr> <td data-bbox="342 767 421 815">1</td> <td data-bbox="421 767 499 815">1</td> <td data-bbox="499 767 577 815">1</td> <td data-bbox="577 767 1283 815"></td> <td data-bbox="1283 767 1361 815">1</td> </tr> </tbody> </table>	A	B	C	Working space	X	0	0	0		1	0	0	1		1	0	1	0		1	0	1	1		1	1	0	0		0	1	0	1		1	1	1	0		1	1	1	1		1	4
A	B	C	Working space	X																																											
0	0	0		1																																											
0	0	1		1																																											
0	1	0		1																																											
0	1	1		1																																											
1	0	0		0																																											
1	0	1		1																																											
1	1	0		1																																											
1	1	1		1																																											

Question	Answer	Marks
7	<p>Compiler</p> <p>Any three from:</p> <ul style="list-style-type: none"> – Translates high-level language into machine code/low level language – Translates (the source code) all in one go/all at once – Produces an executable file – Produces an error report <p>Interpreter</p> <p>Any three from:</p> <ul style="list-style-type: none"> – Translates high-level language into machine code/low level language – Translates (the source code) line by line/statement by statement – Stops if it finds an error – Will only continue when error is fixed 	6

Question	Answer	Marks
8(a)	<p>Any four from:</p> <ul style="list-style-type: none"> – Shines light / (red) laser at barcode – Light is called an illuminator – Light is reflected back // White lines reflect light // Black lines reflect less light/absorbs light – Sensors / photoelectric cells detect the light – Different reflections / bars will give different binary values / digital values // pattern converted to digital values – A microprocessor interprets the data 	4
8(b)	<p>Any three from:</p> <ul style="list-style-type: none"> – barcode identifies a (unique) product – barcode can be used to look up product (in a database) – data about stock levels can be stored on a system – stock can be automatically deducted from the system – can check stock is below a certain level // check stock level – automatic re-order // Alerts when stock is low – automatically update new stock level – to locate if an item of stock is available in another location 	3

Question	Answer	Marks
8(c)	Any four from: <ul style="list-style-type: none"> – (Infrared) rays are sent across screen (from the edges) – Has sensors around edge // Sensors capture beams – (Infrared) rays form a grid across the screen – (Infrared) ray is broken (by a finger blocking a beam) – Calculation is made (on where beam is broken) to locate the 'touch' // Co-ordinates are used to locate the touch 	4
8(d)	Secondary Storage – any two from: <ul style="list-style-type: none"> – Not directly accessed by the CPU – Non-volatile storage – Secondary is internal to the computer/device – An example of secondary storage would be HDD/SSD Off-line storage – any two from: <ul style="list-style-type: none"> – Non-volatile storage – Off-line storage is storage that is removable from a computer/device // not internal // portable – An example of off-line storage would be CD/DVD/USB stick/SD card/magnetic tape/ external HDD/SSD 	4

Question	Answer	Marks
9	Any six from: <ul style="list-style-type: none"> – Suitable biometric device, such as fingerprint scanner/retina/eye/iris scanner/face recognition/voice recognition/palm scanner // description of use e.g. use fingerprint on device – Sensor (in biometric device) captures/takes data/readings (of user) – Data/readings are converted from analogue to digital (using ADC) – Data/reading sent to the microprocessor – Data/readings compared to stored values/data ... – ... if data/readings match user can enter – ... if data/readings do not match user is declined entry // user asked to try again ... – ... alert may be sent to security // alarm may sound 	6

Question	Answer	Marks
10(a)	Any four from: <ul style="list-style-type: none"> – Structure and presentation are defined using (mark-up) tags – Structure and presentation dictate the appearance of the website – Structure is used for layout – Example of structure – Presentation is used for formatting / style – Example of formatting – Separate file / CSS can be used for presentation content 	4
10(b)(i)	1 mark for each correct part <ul style="list-style-type: none"> – domain (name) – file name/webpage name 	2
10(b)(ii)	Any two from: <ul style="list-style-type: none"> – Hypertext Transfer Protocol Secure // it is the access protocol // It is a protocol – It means the website uses SSL/TLS – It means data sent (to and from the webserver) is encrypted 	2
10(c)	Any two from e.g. : <ul style="list-style-type: none"> – To store items that a customer has added to an online shopping basket – To store a customer's credit card details – To store log-in details – To track what product a customer browses // Track music preferences – Targeted advertising // making recommendations – Personalises/customises the experience – Shows who are new and returning customers – To speed up log-in times – To speed up/allow single click purchases – Improves the experience 	2

Question	Answer	Marks
10(d)	Any four from: <ul style="list-style-type: none">– Prevents direct access to the webserver // Sits between user and webserver– If an attack is launched it hits the proxy server instead // can be used to help prevent DDOS // help prevent hacking of webserver– Used to direct invalid traffic away from the webserver– Traffic is examined by the proxy server // Filters traffic– If traffic is valid the data from the webserver will be obtained by the user– If traffic is invalid the request to obtain data is declined– Can block requests from certain IP addresses	4